



WHEN A LONG RANGE TRANSMITTER / RECEIVER KIT WON'T REACH, TRY THE REIGN TX-100.

The Reign TX-100 / XRE-100 kit allow for triggering a dry contact relay using our proprietary wireless technology and our hand-held transmitter.

Forget about not being able to trigger your gate, door, alarm, or security panel. With the Reign TX-100 far is always reachable.

FEATURES

XRE-100 RECEIVER

- 2 Relays Latching or Momentary (Selectable w/ Jumper)
- Adjustable Delay Between Relays

TX-100 TRANSMITTER

- 9 V Alkaline Battery
- LED Notification for Transmit and Receive Verification
- Adjustable Transmit Power







SPECIFICATIONS

RECEIVER:

Security:

AES128 Wireless Encryption

Operating Power: 12/24V AC/DC 12 V: 50mA (idle), 1A (transmit) 24 V: 25mA (idle), 500mA (transmit)

Dimensions:

Box: 3-3/4"x 5-1/4" x 2"

With Antenna: 3-3/4" x 10-1/2" x 2"

Temperature Range:

-40°F to 185°F (-40°C to 85°C)

Relays:

2 Outputs: 3 Amp 250 v AC

3 Amp 220v DC

2 Inputs

Memory:

150 Transmitters

TRANSMITTER:

Power:

Battery

Dimensions:

2-3/8" x 3-1/2" x 3/4"

CONTACT US

TRANSMITTER SOLUTIONS

PH 866.975.0101 **FX** 866.975.0404

www.transmittersolutions.com

DIMENSIONS



TX-100



